

# Screwdrivers designed for DLR5640-WN

■ Screw Fastening Counter



DLR5640-WE



DLV7410A/7410HA/7420A-SPC



DLV7321/7331-SPC

## Specifications

| Model                           | DLV7410A-SPC              | DLV7410HA-SPC | DLV7420A-SPC | DLV7321-SPC | DLV7331-SPC |
|---------------------------------|---------------------------|---------------|--------------|-------------|-------------|
| Starting Method                 | Lever start switch        |               |              |             |             |
| Torque Adjustment               | Stepless                  |               |              |             |             |
| Torque (N·m)                    | 0.02 - 0.20               |               | 0.15 - 0.40  | 0.10 - 0.50 | 0.30 - 1.20 |
| Free Speed (min <sup>-1</sup> ) | 500 - 750                 | 700 - 1,000   | 450 - 600    | 300 - 1,000 | 200 - 700   |
| Power Consumption (W)           | Approx. 10                |               |              | Approx. 35  |             |
| Screw Size (mm)                 | Machine Screw             | 1.0 - 2.3     |              | 1.0 - 3.0   | 2.0 - 3.5   |
|                                 | Tapping Screw             | 1.0 - 2.0     |              | 1.2 - 2.6   | 2.0 - 3.0   |
| Bit Type (mm)                   |                           |               |              |             |             |
| Electrostatic Countermeasure    | Complied with EN100015-1  |               |              |             |             |
| Mass (g)                        | 230                       |               |              | 350         |             |
| Cord Length (m)                 | 1.5 (with connector)      |               |              |             |             |
| Output Signals                  | Start, Torque up, Reverse |               |              |             |             |
| Grounding Bit Feature           | Equipped as standard      |               |              |             |             |

## Combinations with Electric Screwdrivers

| Screwdriver Model                                    | Connection                                 | Remarks                                          |
|------------------------------------------------------|--------------------------------------------|--------------------------------------------------|
| DLV7410A / 7410HA / 7420A-SPC                        | The cord comes with screwdriver            | Screwdriver for the screw fastening counter only |
| DLV7321 / 7331-SPC                                   | Direct connection to power source          |                                                  |
| DLV7410A / 7410HA / 7420A / 7419 / 7419HA / 7429-BMN | Optional conversion cord (TD02925 DLW9072) | General-purpose screwdriver *1                   |

\*1: The Count Return Function is not available.

## Optional Cord



DLW9072(TD02925)



Conversion cord from 5-prong to 6-prong(TD02826)

DLR5640-WN